

1. The first of these is the fact that the
 2.
 3.
 4.
 5.
 6.
 7.
 8.
 9.
 10.
 11.
 12.
 13.
 14.
 15.
 16.
 17.
 18.
 19.
 20.
 21.
 22.
 23.
 24.
 25.
 26.
 27.
 28.
 29.
 30.
 31.
 32.
 33.
 34.
 35.
 36.
 37.
 38.
 39.
 40.
 41.
 42.
 43.
 44.
 45.
 46.
 47.
 48.
 49.
 50.
 51.
 52.
 53.
 54.
 55.
 56.
 57.
 58.
 59.
 60.
 61.
 62.
 63.
 64.
 65.
 66.
 67.
 68.
 69.
 70.
 71.
 72.
 73.
 74.
 75.
 76.
 77.
 78.
 79.
 80.
 81.
 82.
 83.
 84.
 85.
 86.
 87.
 88.
 89.
 90.
 91.
 92.
 93.
 94.
 95.
 96.
 97.
 98.
 99.
 100.
 101.
 102.
 103.
 104.
 105.
 106.
 107.
 108.
 109.
 110.
 111.
 112.
 113.
 114.
 115.
 116.
 117.
 118.
 119.
 120.
 121.
 122.
 123.
 124.
 125.
 126.
 127.
 128.
 129.
 130.
 131.
 132.
 133.
 134.
 135.
 136.
 137.
 138.
 139.
 140.
 141.
 142.
 143.
 144.
 145.
 146.
 147.
 148.
 149.
 150.
 151.
 152.
 153.
 154.
 155.
 156.
 157.
 158.
 159.
 160.
 161.
 162.
 163.
 164.
 165.
 166.
 167.
 168.
 169.
 170.
 171.
 172.
 173.
 174.
 175.
 176.
 177.
 178.
 179.
 180.
 181.
 182.
 183.
 184.
 185.
 186.
 187.
 188.
 189.
 190.
 191.
 192.
 193.
 194.
 195.
 196.
 197.
 198.
 199.
 200.
 201.
 202.
 203.
 204.
 205.
 206.
 207.
 208.
 209.
 210.
 211.
 212.
 213.
 214.
 215.
 216.
 217.
 218.
 219.
 220.
 221.
 222.
 223.
 224.
 225.
 226.
 227.
 228.
 229.
 230.
 231.
 232.
 233.
 234.
 235.
 236.
 237.
 238.
 239.
 240.
 241.
 242.
 243.
 244.
 245.
 246.
 247.
 248.
 249.
 250.
 251.
 252.
 253.
 254.
 255.
 256.
 257.
 258.
 259.
 260.
 261.
 262.
 263.
 264.
 265.
 266.
 267.
 268.
 269.
 270.
 271.
 272.
 273.
 274.
 275.
 276.
 277.
 278.
 279.
 280.
 281.
 282.
 283.
 284.
 285.
 286.
 287.
 288.
 289.
 290.
 291.
 292.
 293.
 294.
 295.
 296.
 297.
 298.
 299.
 300.
 301.
 302.
 303.
 304.
 305.
 306.
 307.
 308.
 309.
 310.
 311.
 312.
 313.
 314.
 315.
 316.
 317.
 318.
 319.
 320.
 321.
 322.
 323.
 324.
 325.
 326.
 327.
 328.
 329.
 330.
 331.
 332.
 333.
 334.
 335.
 336.
 337.
 338.
 339.
 340.
 341.
 342.
 343.
 344.
 345.
 346.
 347.
 348.
 349.
 350.
 351.
 352.
 353.
 354.
 355.
 356.
 357.
 358.
 359.
 360.
 361.
 362.
 363.
 364.
 365.
 366.
 367.
 368.
 369.
 370.
 371.
 372.
 373.
 374.
 375.
 376.
 377.
 378.
 379.
 380.
 381.
 382.
 383.
 384.
 385.
 386.
 387.
 388.
 389.
 390.
 391.
 392.
 393.
 394.
 395.
 396.
 397.
 398.
 399.
 400.
 401.
 402.
 403.
 404.
 405.
 406.
 407.
 408.
 409.
 410.
 411.
 412.
 413.
 414.
 415.
 416.
 417.
 418.
 419.
 420.
 421.
 422.
 423.
 424.
 425.
 426.
 427.
 428.
 429.
 430.
 431.
 432.
 433.
 434.
 435.
 436.
 437.
 438.
 439.
 440.
 441.
 442.
 443.
 444.
 445.
 446.
 447.
 448.
 449.
 450.
 451.
 452.
 453.
 454.
 455.
 456.
 457.
 458.
 459.
 460.
 461.
 462.
 463.
 464.
 465.
 466.
 467.
 468.
 469.
 470.
 471.
 472.
 473.
 474.
 475.
 476.
 477.
 478.
 479.
 480.
 481.
 482.
 483.
 484.
 485.
 486.
 487.
 488.
 489.
 490.
 491.
 492.
 493.
 494.
 495.
 496.
 497.
 498.
 499.
 500.
 501.
 502.
 503.
 504.
 505.
 506.
 507.
 508.
 509.
 510.
 511.
 512.
 513.
 514.
 515.
 516.
 517.
 518.
 519.
 520.
 521.
 522.
 523.
 524.
 525.
 526.
 527.
 528.
 529.
 530.
 531.
 532.
 533.
 534.
 535.
 536.
 537.
 538.
 539.
 540.
 541.
 542.
 543.
 544.
 545.
 546.
 547.
 548.
 549.
 550.
 551.
 552.
 553.
 554.
 555.
 556.
 557.
 558.
 559.
 560.
 561.
 562.
 563.
 564.
 565.
 566.
 567.
 568.
 569.
 570.
 571.
 572.
 573.
 574.
 575.
 576.
 577.
 578.
 579.
 580.
 581.
 582.
 583.
 584.
 585.
 586.
 587.
 588.
 589.
 590.
 591.
 592.
 593.
 594.
 595.
 596.
 597.
 598.
 599.

INVENTOR

JAMES H. PARRY
P.O. Box 557
Saratoga, CA 95071

DISTORTION COMPENSATION IN AN ACOUSTIC ECHO CANCELER

INVENTOR

JAMES H. PARRY

5

BACKGROUNDFIELD OF THE INVENTION

This invention pertains in general to telephony and televideo conferencing and in particular to performing acoustic echo cancellation on potentially distorted audio signals.

10 BACKGROUND ART

Two-way audio communications systems, such as speakerphones and video communications systems having audio capabilities, utilize both a microphone and a loudspeaker. The microphone transmits speech and other sounds from the local terminal to remote terminals while the loudspeaker emits sounds received from remote terminals.

15 In a typical hands-free system, the loudspeaker and microphone are located in close proximity and sounds produced by the loudspeaker are picked up by the microphone.

Without signal processing, therefore, a feedback loop is easily created between the loudspeaker and microphone. This feedback can cause the loudspeaker to emit an undesirable "howling" noise and cause the remote terminals to hear echoes.

20 One simple technique for eliminating feedback is to provide half-duplex switching where only the microphone or the loudspeaker is active at any given instant. In a typical half-duplex system, the loudspeaker is active until a sound is detected at the microphone. Then, the loudspeaker becomes inactive and the microphone becomes active for the

duration of the sound. Half-duplex systems have many inherent problems, not the least of which is that a slight noise may unintentionally cause the loudspeaker to cut out. As a result, it is often difficult to conduct a normal conversation with a system using half-duplex switching.

5 More sophisticated audio communications systems use acoustic echo cancellation (AEC) to reduce echoes and eliminate howling. An AEC system typically utilizes a sample-by-sample copy of the signal going to the loudspeaker as the basis for an estimate of the echo returning through the microphone, as taught in U.S. Patent No. 4,965,822, entitled FULL DUPLEX SPEAKERPHONE, which issued on October 23, 1990 and is
10 incorporated by reference herein. This estimated echo is subtracted on a sample-by-sample basis in an attempt to separate out only that portion of the microphone signal due to sounds coming from sources other than the speaker. An adaptive AEC uses a filter having slowly adjusted weights to form the echo estimate in an effort to more accurately subtract the echo from the returned audio signal. Subsequent conditioning performed on
15 the output of the AEC may include automatic gain control (AGC) and perceived noise reduction.

A problem with the above approach is that the loudspeakers do not produce sound pressure signals that are exactly proportional to the driving voltage (or current).

Likewise, microphones are imperfect in an analogous sense. There may also be other
20 sources of distortion within the sound system, such as amplifiers, analog-to-digital (A/D) and digital-to-analog (D/A) converters, and perhaps even the user's environment.

Existing AEC systems do not accurately remove the nonlinear components of the returned signal due to these sources of potential distortion. As a result, a badly distorted form of

the echo can pass through the echo cancellation process. Another undesirable effect of these introduced distortions is that the adaptation of the AEC parameters is degraded, leading to a greater perceived echo.

One potential solution to the problem of degraded AEC adaptation is to use a reduced adaptation rate during periods of very loud sound output. This technique is used, for example, in U.S. Application No. 09/XXX,XXX, entitled APPARATUS AND METHOD FOR CONTROLLING AN ACOUSTIC ECHO CANCELER, filed on January 20, 2000, and incorporated by reference herein. However, reducing the adaptation rate has the undesirable effect of slowing the system's response to a changing acoustic environment such as when users are in motion and/or the room temperature fluctuates.

Another potential solution is to use higher quality loudspeakers and other components. This solution, however, carries with it considerable expense and places severe limitations on the designs of the equipment. High-quality loudspeakers are typically large and heavy and generate strong external magnetic fields. Often, the audio communications system is integrated into another sound system, such as the audio subsystem of a laptop computer, where a high-quality loudspeaker cannot be used.

Therefore, there is a need for a technique for more accurately estimating the echo when performing acoustic echo cancellation. There is also a need for a technique for more accurately adapting the estimated echo in response to changing acoustic characteristics.

DISCLOSURE OF THE INVENTION

The above needs are met by using modules to estimate the nonlinear distortions in the audio signal returned from the microphone that were introduced by the loudspeaker, microphone, and related components.

5 A typical audio communications system has a plurality of terminals coupled to a switch. The terminals can include, for example, dedicated speakerphones, desktop handsets with or without speakerphone capabilities, cellular phones, and/or personal computer (PC) systems with audio capabilities. The switch may be dedicated to audio communications, as is a private branch exchange (PBX), or distributed and
10 multifunctional, as is an Internet server.

Each terminal preferably includes a microphone and a loudspeaker. An amplifier amplifies the electrical signals produced by the microphone and provides its output to an A/D converter. The A/D converter outputs equivalent digital samples. The loudspeaker is driven by another amplifier which, in turn, is driven by the output of a D/A converter.
15 The D/A converter receives digital samples representing the sound pressure waves to be produced by the loudspeaker.

In order to cancel echoes of the loudspeaker picked up by the microphone, the audio communications system has an acoustic echo cancellation (AEC) module. The AEC module can be located in the terminal or elsewhere in the audio communications
20 system. U.S. Patent Application No. 09/660,205, entitled COMMUNICATIONS SYSTEM AND METHOD UTILIZING CENTRALIZED SIGNAL PROCESSING, filed on September 12, 2000, and incorporated by reference herein, describes potential

locations of the AEC module. The AEC module preferably receives the digital signal sent to the loudspeaker and the digital signal received from the microphone.

The digital loudspeaker signal is processed by an audio generation module (AGM) to model the substantially nonlinear distortions that can occur during the process of playing the audio signal at the loudspeaker. The AGM includes a modeling path comprised of one or more distortion modules. Each distortion module receives digital samples as input, modifies the samples to model a form of distortion, and outputs the modified samples. A distortion module can be adaptive or it can be partly or wholly pre-established. Preferably, the AGM can add or remove distortion modules from the modeling path at any time in response to characteristics of the digital samples or under direction from other modules. Distortions that can be modeled by the distortion modules in the AGM modeling path include, for example, amplifier clipping, loudspeaker voice coil displacement, harmonic distortion introduced by the loudspeaker, and hysteresis in an iron-core inductor.

The AGM outputs digital sample values to an acoustic echo estimation (AEE) module. The AEE module preferably uses known adaptive algorithms to adapt the digital samples to compensate for substantially linear changes in the echo characteristics of the environment in which the loudspeaker and microphone are located. For example, the AEE module can modify the digital samples to account for changes in echo attenuation due to relocation of people in the vicinity of the microphone.

The output of the AEE module is received by an audio sensing module (ASM). The ASM performs a function similar to the AGM, except that the ASM models substantially nonlinear distortions that occur while sensing the audio signal. Accordingly,

1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------

10

FIGURE 1 is a high-level block diagram of an audio communications system according to an embodiment of the present invention;

FIGURE 2 is a block diagram illustrating various components of the audio communications system including an acoustic echo cancellation (AEC) module; and

15

FIG. 1 is a high-level block diagram of an audio communications system 100 according to an embodiment of the present invention. A plurality of terminals 110A-D are coupled to a switch 112 via communications links 114A-D. The terminal types can be heterogeneous or homogeneous. In one embodiment, the terminals include: dedicated speakerphones, desktop handsets with or without speakerphone capabilities, cellular

phones, and/or personal computer (PC) systems with audio capabilities. As used herein, the phrase "audio communications system" also includes video conferencing systems having audio capabilities. Each terminal 110, of which terminal 110A is representative, preferably includes a microphone 116A and a loudspeaker 118A. As is known in the art,

5 the microphone 116 converts sound pressure waves into electrical signals and the loudspeaker 118 converts electrical signals into sound pressure waves.

The communications links 114 carry audio data representative of sounds picked up by the microphone 116 and to be played by the loudspeaker 118 to/from the switch 112. The communications links 114 may be wired or wireless. Moreover, the links 114

10 may include dedicated private links, shared links utilizing a publicly-accessible telephone network, and/or links using a public or private data communications network such as the Internet. Data traveling over the links 114 may pass through one or more switches or link types before reaching the switch 112 or terminal 110, although a preferred embodiment of the present invention treats a link passing through multiple links and switches as a single

15 logical link. The data carried by the communications links 114 can be digital and/or analog. If the data is digital, it is preferably transmitted as a series of discrete data packets, such as Internet protocol (IP) packets. In one embodiment, the digital data is encoded into a compressed format.

The switch 112 switches and routes communications among the terminals. The

20 switch 112 can be, for example, a private branch exchange (PBX) located at a business or other entity, a publicly-accessible switch operated by a telephone company or other entity providing audio communications, or an Internet server supporting Internet telephony.

Thus, the term "switch" includes any device or combination of devices capable of providing the switching and other functionality attributed to the switch herein.

In one embodiment, the terminals 110 and/or switch 112 have one or more of the components found in a typical computer system, including a processing unit, random
5 access memory (RAM), read-only memory (ROM), a storage device such as a hard drive, and/or other hardware and software for providing the functionality described herein.

Aggregations of machine-executable code, data, circuitry, and/or data storage areas for performing a specific purpose or purposes are referred to as "modules." Different modules may share common code, data, and/or circuitry. The modules include, for
10 example, signal processing modules, digital-to-analog (D/A) and analog-to-digital (A/D) converter modules, and amplifier modules. Modules may hold in their storage areas previous values of signals and current statistics derived therefrom. Modules can also use adaptive techniques, or training, to perform the modules' functionalities. As used herein, the terms "adaptation" and "training" are interchangeable and refer to acting on a signal
15 responsive to previous values of that signal or other signals, statistics derived from the signals, and/or external controls or sensors.

FIG. 2 is a block diagram illustrating various components of the audio communications system including an acoustic echo cancellation (AEC) module 210.

FIG. 2 illustrates the microphone 116 of FIG. 1 having its output coupled to an amplifier

20 212. As is known in the art, the microphone 116 converts sound pressure waves into electrical signals. The amplifier 212 amplifies the electrical signals and provides its output to an A/D converter 214. The A/D converter 214 outputs digital sample values representative of the sound pressure waves to the AEC module 210.

FIG. 2 also illustrates the speaker 118 of FIG. 1. The speaker 118 generates sound pressure waves in response to an input received from an amplifier 216. The amplifier 216, in turn, is driven by the output of a D/A converter 218. The D/A converter 218 receives digital sample values representing the sound pressure waves as input from the link 114 or another source.

In general, the AEC module 210 estimates the echo of sounds played by the loudspeaker 118 that are picked up by the microphone 116, subtracts the estimated echo from the microphone's audio signal, and outputs the resulting echo-cancelled signal. In one embodiment, the AEC module 210 is located in the terminal 110. Accordingly, the output of the AEC module 210 is passed over the communications links 114 to the switch 112. In alternative embodiments, the AEC module 210 is located in the switch 112 or anywhere else that echo cancellation is desired and representations of the loudspeaker and microphone signals are available.

Turning to the AEC module 210 itself, the digital samples representing the audio signal sensed by the microphone output by the A/D converter 214 are received by an adder module 220. The adder module 220 also receives an input 222 providing digital samples representing the echo from the loudspeaker 118 estimated to be present in the microphone signal. The adder module 220 preferably adds the negative of the estimated echo to the signal received from the A/D converter 214. Preferably, the adder module 220 works on a sample-by-sample basis. In one embodiment, both the estimated echo samples received from the input 222 and the sample values received from the A/D converter 214 bear sequencing information that the adder module 220 uses to match the

samples. U.S. Patent Application No. 09/660,205, incorporated by reference herein, discloses additional details related to the sequencing information.

The output of the adder module 220 is passed to a perceived noise reduction module 224. This module 224 preferably reduces perceived noise in the audio signal.

5 Techniques for reducing perceived noise are well known in the art.

The output of the perceived noise reduction module is preferably passed to an automatic gain control (AGC) module 226. As is known in the art, the AGC module 226 preferably isolates times during which local speech is thought to be present in the input signal and adjusts the signal gain so that the speech is near a predetermined level when
10 considered on average. The AGC module 226 can use adaptive techniques to perform AGC. The output 228 of the AGC module 226 is preferably provided to the switch 112 via the communications links 114 as described above.

The AEC module 210 also receives an input 230 carrying digital sample values representing the audio signal being sent to the loudspeaker 118 of the terminal 110. If the
15 AEC module 210 is located in the terminal 110, then this input 230 is received from the switch 112 via the communications links 114. The loudspeaker 118 digital sample values are received by an audio generation module (AGM) 232 within the AEC module 210.

The AGM 232 preferably modifies the digital sample values to model substantially nonlinear distortions that can occur during the process of generating the
20 audio signal. FIG. 3 is a block diagram illustrating a lower-level view of the AGM 232 according to an exemplary embodiment of the present invention. The AGM 232 includes a modeling path 310 comprised of logical interconnects among one or more distortion modules 312 that operate on the digital samples traveling through the path. Each

distortion module 312 receives digital samples as input, modifies the samples to model a form of distortion, and outputs the modified samples. Preferably, the AGM 232 can add or remove distortion modules from the modeling path 310 at any time in response to characteristics of the digital samples or under direction from other modules.

5 The AGM 232 preferably models effects which are substantially nonlinear. Certain embodiments utilize artificial neural networks (ANNs) to achieve adaptation. Those ANNs which are not adaptive may be present at the time of manufacture and do not require feedback for further adaptation. ANNs in adaptive modules 312 utilize internal and/or external feedback. Such feedback may be from other distortion modules 10 312, from the loudspeaker digital signal, and/or from the microphone signal before or after the adder module 220. These many possible feedback paths have been omitted from the modeling path 310 in FIG. 3 in order to clarify the teachings of the present invention.

 The example of a modeling path 310 illustrated in the AGM 232 of FIG. 3 has three distortion modules 312A, 312B, 312C arranged in sequence. Each distortion 15 module 312 preferably contains a filter or other operator that acts on the input samples. The module 312 can be adaptive or it can be partly or wholly pre-established. Likewise, the module 312 can operate in the time or frequency domains. The module 312 can also act in response to short or long-term signal characteristics to model effects such as heat build-up.

20 Preferably, each distortion module 312 independently models a form of distortion. In FIG. 3, the first distortion module 312A models amplifier clipping by enforcing a hard limit on signal amplitudes. Thus, this distortion module 312A models the effects of the speaker amplifier 216 in the terminal 110 on the analog signal sent to the loudspeaker

118. The second distortion module 312B models loudspeaker 118 voice coil (or equivalent structure) displacement. In one embodiment, this distortion module 312B estimates the nonlinear relationship between the voice coil displacement and the driving current. In one embodiment, the driving current estimate received by the voice coil displacement module 312B is generated by the amplifier clipping module 312A and so may be a nonlinear representation of the loudspeaker digital samples. The third distortion module 312C models harmonic distortion introduced by the loudspeaker 118. In one embodiment, this distortion module 312C applies harmonic distortion with a strength modulated by the energy in the spectral components subject to the distortion. Thus, this distortion module 312C mimics the operation of a loudspeaker 118 driven with high electrical amplitudes where diaphragms distort and resonate. Other distortion modules 312 that may be utilized in the modeling path 310 include modules that account for distortions introduced by the D/A conversion module 218 and modules that account for hysteresis in iron core inductors.

In one embodiment of the present invention, the distortion modules 312 are tailored to model the distortions introduced by specific types of hardware. For example, if the AGM 232 is located in the terminal 110, the amplifier clipping 310A and voice coil displacement 310B modules can be specifically tailored for the amplifiers and voice coils included in the terminal 110.

The AGM 232 outputs digital sample values representing the distorted audio signal to an acoustic echo estimation (AEE) module 234. The AEE module 234 preferably uses adaptive algorithms to adapt the digital samples to compensate for substantially linear changes in the echo characteristics of the environment in which the

loudspeaker 118 and microphone 116 are located. For example, the AEE module 234 can modify the digital samples to account for changes in echo attenuation due to relocation of people in the vicinity of the microphone 116.

The digital sample values output by the AEE module 234 are preferably received
5 by an audio sensing module (ASM) 236. The ASM 236 preferably modifies the digital sample values to model distortions that can occur in the process of sensing the audio signal. Like the AGM 232, the ASM 236 preferably includes a modeling path comprised of logical interconnects among one or more distortion modules. The modeling path for the ASM 236 is not shown in the figures because it would be redundant in view of FIG. 3.

10 Also like the AGM 232, the ASM 236 preferably models substantially nonlinear distortions. Unlike the AGM 232, the ASM preferably models distortions such as microphone 116 centerclipping, amplifier zero crossing distortion, saturation in either the microphone or the amplifier, and/or distortions introduced by the A/D converter 214. The output of the ASM 236 is provided to the adder module 220 and becomes the input signal
15 representing the echo from the loudspeaker 118 estimated to be present in the microphone signal described above.

Accordingly, the AEC module 210 of the present invention accurately models the effects of distortion on the audio signals. The modeled types of distortion include nonlinear distortions introduced while generating and sensing the audio signal and linear
20 echoes introduced responsive to room characteristics. This distortion modeling enables the AEC to more accurately cancel the echo in the signal received from the microphone 116.

The above description is included to illustrate the operation of the preferred embodiments and is not meant to limit the scope of the invention. The scope of the invention is to be limited only by the following claims. From the above discussion, many variations will be apparent to one skilled in the relevant art that would yet be

5 encompassed by the spirit and scope of the invention.